

SANYO Semiconductors DATA SHEET

N-Channel Silicon MOSFET

FSS273 — General-Purpose Switching Device **Applications**

Features

- · Motor drive applications.
- · Inverter drive applications.
- 4V drive.

Specifications

Absolute Maximum Ratings at Ta=25°C

Parameter	Symbol	Conditions	Ratings	Unit
Drain-to-Source Voltage	VDSS		45	V
Gate-to-Source Voltage	VGSS		±20	٧
Drain Current (DC)	ΙD		8	Α
Drain Current (PW≤10s)	ID	Duty cycle≤1%	8.5	Α
Drain Current (PW≤10μs)	IDP	Duty cycle≤1%	32	Α
Allowable Power Dissipation	PD	Mounted on a ceramic board (1200mm²X0.8mm), PW≤10s	2.4	W
Channel Temperature	Tch		150	°C
Storage Temperature	Tstg		-55 to +150	°C

Electrical Characteristics at Ta=25°C

Parameter	Symbol	Conditions	Ratings			11.7
			min	typ	max	Unit
Drain-to-Source Breakdown Voltage	V(BR)DSS	ID=1mA, VGS=0V	45			V
Zero-Gate Voltage Drain Current	IDSS	V _{DS} =45V, V _{GS} =0V			1	μΑ
Gate-to-Source Leakage Current	IGSS	VGS=±16V, VDS=0V			±10	μΑ
Cutoff Voltage	VGS(off)	V _{DS} =10V, I _D =1mA	1.2		2.6	V
Forward Transfer Admittance	yfs	V _{DS} =10V, I _D =8A	6	10		S
Static Drain-to-Source On-State Resistance	RDS(on)1	ID=8A, VGS=10V		16	22	mΩ
	R _{DS} (on)2	I _D =4A, V _{GS} =4V		24	34	mΩ
Input Capacitance	Ciss	V _{DS} =20V, f=1MHz		2225		pF
Output Capacitance	Coss	V _{DS} =20V, f=1MHz		260		pF
Reverse Transfer Capacitance	Crss	V _{DS} =20V, f=1MHz		190		pF
Turn-ON Delay Time	t _d (on)	See specified Test Circuit.		27		ns
Rise Time	tr	See specified Test Circuit.		55		ns
Turn-OFF Delay Time	t _d (off)	See specified Test Circuit.		150		ns
Fall Time	tf	See specified Test Circuit.		80		ns

Marking: S273 Continued on next page.


- Any and all SANYO Semiconductor products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your SANYO Semiconductor representative nearest you before usingany SANYO Semiconductor products described or contained herein in such
- SANYO Semiconductor assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO Semiconductor products described or contained herein.

Continued from preceding page.


Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max] Oill
Total Gate Charge	Qg	V _{DS} =24V, V _{GS} =10V, I _D =8A		40		nC
Gate-to-Source Charge	Qgs	V _{DS} =24V, V _{GS} =10V, I _D =8A		6		nC
Gate-to-Drain "Miller" Charge	Qgd	V _{DS} =24V, V _{GS} =10V, I _D =8A		8		nC
Diode Forward Voltage	VSD	IS=8A, VGS=0V		0.82	1.2	V


Package Dimensions


unit: mm 7005-002




Switching Time Test Circuit









Note on usage: Since the FSS273 is a MOSFET product, please avoid using this device in the vicinity of highly charged objects.

- Specifications of any and all SANYO Semiconductor products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Semiconductor Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO Semiconductor products (including technical data,services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of SANYO Semiconductor Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO Semiconductor product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO Semiconductor believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of February, 2006. Specifications and information herein are subject to change without notice.