



Product information

Weller®

WAD 101

Code No. : **T0053266699**

Hot Air Station Set

Hot air station digital 150 W, 230 V, compressed air or inert gas operated

Power unit PU WAD 101 (150 W), hot air iron HAP 1 (100 W, 24 V), hot air nozzle R 06, safety rest KH 27, and hot air nozzle R 04

Technical Data



This station is ESD safe.

Dimensions L x W x H:	166 x 134 x 101 mm
Weight:	approx. 6,7 kg
Channels:	1
Power supply:	230 V
Power consumption:	150W
Fuse:	Fuse: overcurrent release 1,6 A 230 V:T 630 mA / 120 V:T: 1,0 A
Protection class:	I
Temperature range:	°CVersion: Hot air: 50°C - 550°C Soldering iron: 50°C - 450°C °FVersion: Hot air: 122°F - 999°F Soldering iron: 122°F - 850°F
Temperature accuracy:	± 9°C (± 17°F) Hot air: ± 30°C (± 54°F) Soldering iron: ± 9°C (± 17°F)
Temperature accuracy HAP 1:	± 30°C (± 54°F)
Temperature stability:	± 2°C (± 5°F)

Air volume:	ca. 0 - 10 l/min
Pressure:	Pressure input, 400 kPa (58 psi), oilfree, dry compressed air or inert gas N ₂
Vacuum:	no

Weller®